

Understanding Serial Digital Video Bit Rates

National Semiconductor
Application Note 1943
John Jones
April 22, 2009



1.0 Introduction

The technical requirements for digital transport of video signals are described in standards issued by the Society of Motion Picture and Television Engineers (SMPTE). Transport of these signals over point-to-point serial links is referred to as Serial Digital Interface (SDI) and is specified by, among others, SMPTE 259M (standard definition video signals), SMPTE 292M (high definition video signals), and SMPTE 424M (3 Gb/s high definition video signals). These standards originally envisioned only the transport of uncompressed digital video; since their publication they have been adapted to standardize the transport of other signals and other types of data.

Because SDI was designed to apply to a very narrowly-defined class of signals the transport protocols are quite straightforward. The objective of this application note is to explain the basis for the bit rates used in SDI. This will lead to a deeper intuitive understanding of the nature of the SDI signal. Understanding the SDI signal will help the engineer design robust serial digital video systems.

2.0 Elements of a Video Signal

For a full explanation of the generation and characteristics of an analog video signal the reader is referred to any of several excellent references on the subject [1] [2] [3]. Encoding a moving image in the form of an electronic signal is actually quite complex due to the many ways in which it might be (and has been) accomplished. This application note focuses on just a few of these encoding schemes, but the reader should bear in mind that many other schemes exist. The general principles described in this application note can be applied to most of these schemes in a straightforward manner.

A color television picture can be encoded in any of a number of color spaces. The Red-Green-Blue (RGB) color space, for example is widely used. Three signals are required to encode a color television picture in this color space, each containing the instantaneous amplitude of one of the color components as a function of time.

The first television receivers did not display color pictures. When color television signal encoding became widespread it was defined so that black-and-white television receivers could display the color television pictures (albeit in black and white). So a color space was used that divides the color components between a luminance, or brightness, channel (which is all that black-and-white television receivers can display) and two chrominance, or color difference, channels. This is the YCbCr color space. Luminance is often designated by luma and chrominance by chroma.

For broadcast television, the video signal is modulated onto an RF carrier. This modulated carrier is what is transmitted by the television transmitter. The baseband signal imposed on

this carrier consists of (1) the luminance signal encoding the brightness variation of each pixel in the video raster and (2) a color subcarrier centered at approximately 3.58 MHz onto which are modulated, using I/Q Modulation, both chrominance signals. A black-and-white television receiver removes the RF carrier, producing a baseband signal, and then filters out (or just ignores) the color subcarrier, producing the luminance signal which is all it can display.

The above descriptions hold for NTSC broadcast television, used in the United States until June, 2009. Other systems are used elsewhere, but the basic ideas are the same. The chrominance signals are easily separated from the luminance signal. The chrominance signal generally has a narrower bandwidth than the luminance signal because it encodes information for which the human eye has less spatial resolution. Other elements of the television picture encoding scheme such as vertical and horizontal blanking, timing reference signals, color subcarrier reference signals, etc. are described in the references.

3.0 Digitizing a Video Signal

This suggests some simple ways in which one might digitize a video signal. One possibility is to sample the baseband signal including the color subcarrier. This is called composite sampling. A second possibility is to digitize each of the components of the signal in turn and interleave the samples. This is called component sampling. One could also envision digitizing either the luminance and chrominance components described above or the underlying individual color signals.

Since the chrominance components carry less information than the luminance component it is possible to sample them at a lower sample frequency than the luminance component. This is not true if the RGB color space is used and the individual color components are digitized.

All of these methods are supported in SDI. This, in essence, is what an SDI signal is. It is a digitized video signal including very little extra information. The bit rate used to transmit this information is determined by the video content.

It is significant that so little extra information is required for SDI signals. Address headers are not necessary since transmission is from a single source to a single receiver (point-to-point) or from a single source to multiple receivers (multi-drop). Error correction overhead is minimal since the channel is well-controlled and single bit errors may not even be noticed in the displayed video signal. Timing reference signals, which are also present in the analog video signal, are always included. Error Detection and Handling information may be included [4]. Most of the signal, though, is just digitized video information. The sampling and serialization process is represented graphically in *Figure 1*.



FIGURE 1. Graphical Representation of the Sampling and Serialization Scheme for SDI Video

4.0 Derivation of the SDI Bit Rate

An Excel® spreadsheet showing example bit rate calculations is available from the National Semiconductor web site: <http://www.national.com/sdi>. An example of the calculations from this spreadsheet is shown below in Figure 2.

The key elements to be considered when using the spreadsheet are as follows:

1. whether the signal is digitized as composite video or component video (there are standards for digitizing YCbCr and RGB components)
2. whether the signal is interlaced or progressive
3. whether the frame rate is 50 Hz, 60 Hz, or 60/1.001 Hz
4. the number of lines per frame
5. the sampling rate

Many serial video formats use 10-bit samples. SMPTE 425M and SMPTE 274M call out a 12-bit sample standard. One example of a video standard with 10-bit samples is 1080p60. When the signal is interlaced, two fields are transmitted for each frame of video. For a progressive signal, each frame of video is transmitted as a single field. The 1080p60 standard, for example, calls out a progressive video standard which transmits each frame of video as a single field, at 60 frames and 60 fields per second.

Notice that for video formats digitized as composite video there is only one sample rate – the composite video signal is digitized at that sample rate. For component video there are (sometimes) two sample rates – one for the luma component and one for the chroma components. Where the chroma components are sampled at half the sampling rate of the luma components this is called a 4:2:2 sampling structure for historical reasons. Where the sample rates are the same for the luma and chroma components this is called a 4:4:4 sampling structure. The standard 1080p60, for example, has a 4:2:2 sampling structure. The number of lines per frame is related to, but not identical to, familiar video standards – for example, 1080p60 has 1125 lines per frame. *Only 1080 of them are visible.*

The sampling rate for the signal is chosen so that the signal can be sampled without aliasing. The information content of each component determines the required bandwidth for each component. The information content is determined by the number of samples per video line, the number of video lines per frame, and the frame rate. For 1080p60, for example, the

luma component is sampled at 148.5 MHz and each of the two chroma components at 74.25 MHz [5].

Using the elements above the bit rate can be calculated. The following symbols are used in the calculations.

N_f = number of fields per frame — this is 2 for interlaced formats, 1 for progressive formats

R_f = frame rate in Hz (frames/second)

R_{field} = field rate in Hz (fields/seconds) = $R_f \times N_f$

N_l = number of lines per frame

N_s = number of samples per line

f_s = sampling rate in number of samples/second for composite video signals

f_{sl} = luma component sampling rate in number of samples/second

f_{sc} = chroma component sampling rate in number of samples/second

N_b = number of bits per sample (10 bits/sample for all the video formats in)

R_b = bit rate in bits/second

For composite sampled video, the bit rate is just the number of bits per sample times the number of samples per second.

$$R_b = N_b \times f_s$$

For component sampled video, the bit rate is just the number of bits per sample times the sum of the number of luma samples per second and twice the number of chroma samples per second (assuming 4:2:2 sampling structure).

$$R_b = N_b \times (f_{\text{sl}} + 2f_{\text{sc}})$$

The number of samples per line, not all of which will be visible, is given by the following for component video signals (assuming a 4:2:2 sampling structure).

$$N_s = \frac{(f_{\text{sl}} + 2f_{\text{sc}})}{N_l \times R_f}$$

30090810

It is possible to have the number of samples per line available but not the sampling rate. In this case, the bit rate is given by the following:

$$R_b = N_b \times N_l \times R_f \times N_s$$

SDI Video Bit Rates															
Signal Type/Sampling Structure	SMPTE Standard	Raster Standard	Video Signal Type	Fields/frame	Number of lines/frame	Field Rate	Frame Rate	Sample Rate	Luma or R'G'B' Sample Rate	Chroma Sample Rate	Samples per Line	Parallel Video Bits	Number Samples/Line	Bit Rate	Bit Rate (Mbps)
NTSC Composite	SMPTE 259M-1997	525i	4fsc (composite)	2.00	525	59.94 (comp)	29.97003	1.43E+07			910	10	910	143181818.2	143.1818182
	SMPTE 244M-2003														
PAL Composite	SMPTE 259M-1997	625i50	4fsc (composite)	2.00	625	50.00 (comp)	25	1.77E+07			1133	10	1135	177343750	177.34375
	IEC 1179														
4:2:2 Component	SMPTE 259M-1997	525i	YCrCb (component)	2.00	525	59.94 (comp)	29.97003		1.35E+07	6.75E+06	1716	10	1716	270000000	270
	SMPTE 259M-1997	625i50	YCrCb (component)	2.00	625	50.00 (comp)	25		1.35E+07	6.75E+06	1728	10	1728	270000000	270
4:2:2 Component	SMPTE 259M-1997	525i	YCrCb (component)	2.00	525	59.94 (comp)	29.97003		1.80E+07	9.00E+06	2288	10	2288	360000000	360
	SMPTE 267M-1995														
4:2:2 Component	SMPTE 344M-2000	525i	YCrCb (component)	2.00	525	59.94 (comp)	29.97003		2.70E+07	1.35E+07	3432	10	3432	540000000	540
	SMPTE 292M-1998	1080i60 (1080i59.9)	YCrCb (component)	2.00	1125	59.94 (comp)	29.97003		7.4176E+07	3.7088E+07	4400	10	4400	1483516484	1483.516484
4:2:2 Component	SMPTE 292M-1998	1080i60	YCrCb (component)	2.00	1125	60.00 (comp)	30		7.4250E+07	3.7125E+07	4400	10	4400	1485000000	1485
	SMPTE 274M-1998														
4:2:2 Component	SMPTE 292M-1998	1080i50	YCrCb (component)	2.00	1125	50.00 (comp)	25		7.4250E+07	3.7125E+07	5280	10	5280	1485000000	1485
	SMPTE 274M-1998														
4:2:2 Component	SMPTE 292M-1998	720p60 (720p59.9)	YCrCb (component)	1.00	750	59.94 (comp)	59.94006		7.4176E+07	3.7088E+07	3300	10	3300	1483516484	1483.516484
	SMPTE 296M-2001														
4:2:2 Component	SMPTE 292M-1998	720p60	YCrCb (component)	1.00	750	60.00 (comp)	60		7.4250E+07	3.7125E+07	3300	10	3300	1485000000	1485
	SMPTE 296M-2001														
4:2:2 Component	SMPTE 292M-1998	720p50	YCrCb (component)	1.00	750	50.00 (comp)	50		7.4250E+07	3.7125E+07	3960	10	3960	1485000000	1485
	SMPTE 296M-2001														
4:2:2 Component	SMPTE 424M-2005	1080p60 (1080p59.9)	YCrCb (component)	1.00	1125	59.94 (comp)	59.94006		1.4835E+08	7.4176E+07	4400	10	4400	2967032967	2967.032967
	SMPTE 425M-2005														
4:2:2 Component	SMPTE 424M-2005	1080p60	YCrCb (component)	1.00	1125	60.00 (comp)	60		1.4850E+08	7.4250E+07	4400	10	4400	2970000000	2970
	SMPTE 425M-2005														
4:2:2 Component	SMPTE 424M-2005	1080p50	YCrCb (component)	1.00	1125	50.00 (comp)	50		1.4850E+08	7.4250E+07	5280	10	5280	2970000000	2970
	SMPTE 425M-2005														
4:4:4 Component	SMPTE 424M-2005	720p60	R'G'B'+A (component)	1.00	750	60.00 (comp)	60		7.4250E+07	7.4250E+07	6600	10	6600	2970000000	2970
	SMPTE 296M-2001														
4:4:4 Component	SMPTE 424M-2005	1080i60	R'G'B'+A (component)	2.00	1125	60.00 (comp)	30		7.4250E+07	7.4250E+07	8800	10	8800	2970000000	2970
	SMPTE 274M-2005														

30090803

FIGURE 2. Example Results for Bit Rate Calculation

5.0 Conclusion

Serial Digital Interface bit rates can be computed in a simple manner from the characteristics of the video signals to be transmitted. This is a simple, but profound, characteristic of SDI signals. Understanding the basis for the bit rates of SDI signal provides valuable insight into how these signals are generated, transported, and displayed.

6.0 References

1. Bernard Grob and Charles E. Herndon, *Basic Television and Video Systems*, Sixth Edition (Westerville, OH: McGraw Hill, 1999).
2. Keith Jack, *Video Demystified* (San Diego, CA: HighText Interactive, Inc., 1996).
3. National Semiconductor Corp., *Broadcast Video Owners Manual*, First Edition (Santa Clara, CA: National Semiconductor Corp., 2004).
4. Michael Robin and Michael Poulin, *Digital Television Fundamentals*, Second Edition (New York, NY: McGraw-Hill, 2000).
5. Society of Motion Picture and Television Engineers, *SMPTE274M-2005; for Television 1920 x 1080 Image Sample Structure, Digital Representation and Digital Timing Reference Sequences for Multiple Picture Rates* (Society of Motion Picture and Television Engineers, 2005).

Notes

For more National Semiconductor product information and proven design tools, visit the following Web sites at:

Products		Design Support	
Amplifiers	www.national.com/amplifiers	WEBENCH® Tools	www.national.com/webench
Audio	www.national.com/audio	App Notes	www.national.com/appnotes
Clock and Timing	www.national.com/timing	Reference Designs	www.national.com/refdesigns
Data Converters	www.national.com/adc	Samples	www.national.com/samples
Interface	www.national.com/interface	Eval Boards	www.national.com/evalboards
LVDS	www.national.com/lvds	Packaging	www.national.com/packaging
Power Management	www.national.com/power	Green Compliance	www.national.com/quality/green
Switching Regulators	www.national.com/switchers	Distributors	www.national.com/contacts
LDOs	www.national.com/ldo	Quality and Reliability	www.national.com/quality
LED Lighting	www.national.com/led	Feedback/Support	www.national.com/feedback
Voltage Reference	www.national.com/vref	Design Made Easy	www.national.com/easy
PowerWise® Solutions	www.national.com/powerwise	Solutions	www.national.com/solutions
Serial Digital Interface (SDI)	www.national.com/sdi	Mil/Aero	www.national.com/milaero
Temperature Sensors	www.national.com/tempsensors	SolarMagic™	www.national.com/solarmagic
Wireless (PLL/VCO)	www.national.com/wireless	Analog University®	www.national.com/AU

THE CONTENTS OF THIS DOCUMENT ARE PROVIDED IN CONNECTION WITH NATIONAL SEMICONDUCTOR CORPORATION ("NATIONAL") PRODUCTS. NATIONAL MAKES NO REPRESENTATIONS OR WARRANTIES WITH RESPECT TO THE ACCURACY OR COMPLETENESS OF THE CONTENTS OF THIS PUBLICATION AND RESERVES THE RIGHT TO MAKE CHANGES TO SPECIFICATIONS AND PRODUCT DESCRIPTIONS AT ANY TIME WITHOUT NOTICE. NO LICENSE, WHETHER EXPRESS, IMPLIED, ARISING BY ESTOPPEL OR OTHERWISE, TO ANY INTELLECTUAL PROPERTY RIGHTS IS GRANTED BY THIS DOCUMENT.

TESTING AND OTHER QUALITY CONTROLS ARE USED TO THE EXTENT NATIONAL DEEMS NECESSARY TO SUPPORT NATIONAL'S PRODUCT WARRANTY. EXCEPT WHERE MANDATED BY GOVERNMENT REQUIREMENTS, TESTING OF ALL PARAMETERS OF EACH PRODUCT IS NOT NECESSARILY PERFORMED. NATIONAL ASSUMES NO LIABILITY FOR APPLICATIONS ASSISTANCE OR BUYER PRODUCT DESIGN. BUYERS ARE RESPONSIBLE FOR THEIR PRODUCTS AND APPLICATIONS USING NATIONAL COMPONENTS. PRIOR TO USING OR DISTRIBUTING ANY PRODUCTS THAT INCLUDE NATIONAL COMPONENTS, BUYERS SHOULD PROVIDE ADEQUATE DESIGN, TESTING AND OPERATING SAFEGUARDS.

EXCEPT AS PROVIDED IN NATIONAL'S TERMS AND CONDITIONS OF SALE FOR SUCH PRODUCTS, NATIONAL ASSUMES NO LIABILITY WHATSOEVER, AND NATIONAL DISCLAIMS ANY EXPRESS OR IMPLIED WARRANTY RELATING TO THE SALE AND/OR USE OF NATIONAL PRODUCTS INCLUDING LIABILITY OR WARRANTIES RELATING TO FITNESS FOR A PARTICULAR PURPOSE, MERCHANTABILITY, OR INFRINGEMENT OF ANY PATENT, COPYRIGHT OR OTHER INTELLECTUAL PROPERTY RIGHT.

LIFE SUPPORT POLICY

NATIONAL'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS PRIOR WRITTEN APPROVAL OF THE CHIEF EXECUTIVE OFFICER AND GENERAL COUNSEL OF NATIONAL SEMICONDUCTOR CORPORATION. As used herein:

Life support devices or systems are devices which (a) are intended for surgical implant into the body, or (b) support or sustain life and whose failure to perform when properly used in accordance with instructions for use provided in the labeling can be reasonably expected to result in a significant injury to the user. A critical component is any component in a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system or to affect its safety or effectiveness.

National Semiconductor and the National Semiconductor logo are registered trademarks of National Semiconductor Corporation. All other brand or product names may be trademarks or registered trademarks of their respective holders.

Copyright© 2009 National Semiconductor Corporation

For the most current product information visit us at www.national.com



**National Semiconductor
Americas Technical
Support Center**
Email: support@nsc.com
Tel: 1-800-272-9959

**National Semiconductor Europe
Technical Support Center**
Email: europe.support@nsc.com

**National Semiconductor Asia
Pacific Technical Support Center**
Email: ap.support@nsc.com

**National Semiconductor Japan
Technical Support Center**
Email: jpn.feedback@nsc.com