Replacing the CLC001 Cable Driver with the LMH0001

National Semiconductor Application Note 2059 Gary Melchior May 11, 2010



Introduction

The LMH0001 SD-SDI cable driver can replace the CLC001 cable driver in many applications. The LMH0001 and CLC001 are both cable drivers designed to drive 75 Ω coaxial cable, primarily for the SMPTE 259M interface. The supported data rates are similar between the two devices. Both cable drivers are powered from a 3.3V supply and rated for industrial temperature range operation (-40°C to +85°C).

The LMH0001, the newer generation SDI cable driver, has improved performance and is pin compatible with the

LMH0002 HD/SD-SDI cable driver and the LMH0302 3G/HD/ SD-SDI cable driver. This allows a forward migration path from SD to HD to 3G. The LMH0001 provides improved output return loss along with a 46% power savings over the CLC001, with typical power of 125 mW in comparison with 231 mW for the CLC001.

Table 1 shows the key differences between the CLC001 and LMH0001.

	CLC001	LMH0001	
Supply Current (I _{CC}) (Typical)	70 mA	38 mA	
Package	8-pin SOIC	16-pin LLP	
Data Rates	DC to 622 Mbps	DC to 540 Mbps	
Output Rise/Fall Time (Typical)	400 ps	400 ps 560 ps	
ESD Rating	≥±7 kV HBM	≥±5 kV HBM	
Input Interface	0.05V to 3.25V common mode	$1.6V + V_{SDI}/2$ to $V_{CC} - V_{SDI}/2$ common mode (self biased)	
Output Interface	Requires external 75Ω resistor to GND	Requires external 75 Ω resistor to V _{CC}	
R _{REF} Resistor (800 mV _{P-P} Output)	1.91 k Ω to ground	750 Ω to V _{CC}	
Output Return Loss	Compliant to SMPTE spec	liant to SMPTE spec Meets SMPTE spec with margin using recommended network	

TABLE 1. CLC001 and LMH0001 Key Differences

How To Replace the CLC001 with the LMH0001

Replacing the CLC001 with the LMH0001 requires a few simple steps. The device packages and pinouts are different so this change requires a new PCB layout. To replace the CLC001 with the LMH0001, follow these steps:

- Check the output common mode voltage of the driving device to determine if it is compatible with the LMH0001 input common mode range—if so, it is preferred to DC couple the inputs, and if not, add AC coupling capacitors in series with the inputs, prior to the input termination. When AC coupling, remove any bias applied to the inputs as this is not required for the LMH0001 since the inputs are self-biased.
- 2. Replace the 75 Ω resistors to ground on the output with 75 Ω resistors to V_{CC}. These pullup resistors should be placed as close as possible to the LMH0001 output pins.

- 3. In order to meet the SMPTE return loss specification, add a return loss network in series with the LMH0001 outputs. This network typically consists of a 5.6 nH inductor in parallel with a 75 Ω resistor, immediately following the 75 Ω pullup. If only one output is used, the return loss network is not necessary on the unused output.
- 4. For SMPTE applications, change the output coupling capacitor from 1 μ F to 4.7 μ F. Using this larger AC coupling capacitor value is good practice when dealing with the large DC shifts associated with the SMPTE pathological signals.
- 5. For 800 mV_{P-P} output, change the R_{REF} resistor from 1.91 k Ω connected to ground to 750 Ω connected to V_{CC}. For 1.0 V_{P-P} output, change the R_{REF} resistor from 1.5 k Ω connected to ground to 590 Ω connected to V_{CC}.

Figure 1 shows the typical application for the CLC001, and *Figure 2* shows the typical application for the LMH0001.









INPUT INTERFACE

The input common mode voltage range of the CLC001 is between 0.05V and 3.25V, and the minimum differential input amplitude is 100 mV. The CLC001 inputs require a DC bias voltage to be applied when the inputs are AC coupled, and the V_{BB} pin may be used for this. When driven differentially, the CLC001 inputs are typically terminated with a 100 Ω resistor placed across the input pins, or two 50 Ω resistors with a center tap capacitor to ground.

The LMH0001 input interface is similar to that of the CLC001, but it does not support rail-to-rail inputs like the CLC001. The input common mode voltage range of the LMH0001 is from $1.6V + V_{SDI}/2$ to $V_{CC} - V_{SDI}/2$, with the same minimum differ-

ential input amplitude as the CLC001. The LMH0001 inputs are self-biased, so no DC bias voltage is necessary when the inputs are AC coupled. When driven differentially, the LMH0001 inputs are typically terminated with a 100 Ω resistor or two 50 Ω resistor like the CLC001.

OUTPUT INTERFACE

The CLC001 outputs are designed to drive 75 Ω AC-coupled coaxial cable. They are current mode and ground referenced, requiring 75 Ω resistors to ground to generate the output voltage. The output level is controlled by the R_{REF} resistor.

The LMH0001 outputs are also current mode and designed to drive 75 Ω AC-coupled coaxial cable. But the LMH0001

outputs are positive supply referenced and require 75 Ω pullups to V_{CC} to generate the output voltage. Like the CLC001, the LMH0001 output level is controlled by the R_{REF} resistor.

OUTPUT LEVEL CONTROL (R_{REF} RESISTOR)

The R_{REF} resistor controls the output driver amplitude. The output amplitude for both the CLC001 and LMH0001 is adjustable from below 800 mV_{P,P} to above 1.0 V_{P,P}. For the CLC001, the R_{REF} resistor is connected to ground, and for the LMH0001, the R_{REF} resistor is connected to V_{CC}. The output amplitude is inversely proportional to the value of R_{REF} and approximately linear. For the CLC001, R_{REF} is 1.91 kΩ for 800 mV_{P,P} output and 1.5 kΩ for 1.0 V_{P,P} output. For the LMH0001, R_{REF} is 750Ω for 800 mV_{P,P} output and 590Ω for 1.0 V_{P,P} output.

OUTPUT RETURN LOSS

The LMH0001 output structure provides improved return loss over the output structure used for the CLC001. This allows

the LMH0001 to exceed the SMPTE return loss specification on the SD001SQ evaluation board with the recommended return loss network consisting of a 5.6 nH inductor in parallel with a 75 Ω resistor. Return loss is dependent on board design so this return loss network may need to be optimized depending on the specific PCB design and BNC connector used.

LMH0001 Enhancements over the CLC001

The LMH0001 is a solid upgrade and good replacement for the CLC001. It is designed in a newer, more advanced process. The LMH0001 offers much lower power and better output return loss. The LMH0001's smaller, space-saving package allows for more compact designs. In addition, the LMH0001's pin compatibility with HD-SDI and 3G-SDI cable drivers offers an easy upgrade path and allows future-proof designs.

Notes

For more National Semiconductor product information and proven design tools, visit the following Web sites at: www.national.com

Products		Design Support		
Amplifiers	www.national.com/amplifiers	WEBENCH® Tools	www.national.com/webench	
Audio	www.national.com/audio	App Notes	www.national.com/appnotes	
Clock and Timing	www.national.com/timing	Reference Designs	www.national.com/refdesigns	
Data Converters	www.national.com/adc	Samples	www.national.com/samples	
Interface	www.national.com/interface	Eval Boards	www.national.com/evalboards	
LVDS	www.national.com/lvds	Packaging	www.national.com/packaging	
Power Management	www.national.com/power	Green Compliance	www.national.com/quality/green	
Switching Regulators	www.national.com/switchers	Distributors	www.national.com/contacts	
LDOs	www.national.com/ldo	Quality and Reliability	www.national.com/quality	
LED Lighting	www.national.com/led	Feedback/Support	www.national.com/feedback	
Voltage References	www.national.com/vref	Design Made Easy	www.national.com/easy	
PowerWise® Solutions	www.national.com/powerwise	Applications & Markets	www.national.com/solutions	
Serial Digital Interface (SDI)	www.national.com/sdi	Mil/Aero	www.national.com/milaero	
Temperature Sensors	www.national.com/tempsensors	SolarMagic™	www.national.com/solarmagic	
PLL/VCO	www.national.com/wireless	PowerWise® Design University	www.national.com/training	

THE CONTENTS OF THIS DOCUMENT ARE PROVIDED IN CONNECTION WITH NATIONAL SEMICONDUCTOR CORPORATION ("NATIONAL") PRODUCTS. NATIONAL MAKES NO REPRESENTATIONS OR WARRANTIES WITH RESPECT TO THE ACCURACY OR COMPLETENESS OF THE CONTENTS OF THIS PUBLICATION AND RESERVES THE RIGHT TO MAKE CHANGES TO SPECIFICATIONS AND PRODUCT DESCRIPTIONS AT ANY TIME WITHOUT NOTICE. NO LICENSE, WHETHER EXPRESS, IMPLIED, ARISING BY ESTOPPEL OR OTHERWISE, TO ANY INTELLECTUAL PROPERTY RIGHTS IS GRANTED BY THIS DOCUMENT.

TESTING AND OTHER QUALITY CONTROLS ARE USED TO THE EXTENT NATIONAL DEEMS NECESSARY TO SUPPORT NATIONAL'S PRODUCT WARRANTY. EXCEPT WHERE MANDATED BY GOVERNMENT REQUIREMENTS, TESTING OF ALL PARAMETERS OF EACH PRODUCT IS NOT NECESSARILY PERFORMED. NATIONAL ASSUMES NO LIABILITY FOR APPLICATIONS ASSISTANCE OR BUYER PRODUCT DESIGN. BUYERS ARE RESPONSIBLE FOR THEIR PRODUCTS AND APPLICATIONS USING NATIONAL COMPONENTS. PRIOR TO USING OR DISTRIBUTING ANY PRODUCTS THAT INCLUDE NATIONAL COMPONENTS, BUYERS SHOULD PROVIDE ADEQUATE DESIGN, TESTING AND OPERATING SAFEGUARDS.

EXCEPT AS PROVIDED IN NATIONAL'S TERMS AND CONDITIONS OF SALE FOR SUCH PRODUCTS, NATIONAL ASSUMES NO LIABILITY WHATSOEVER, AND NATIONAL DISCLAIMS ANY EXPRESS OR IMPLIED WARRANTY RELATING TO THE SALE AND/OR USE OF NATIONAL PRODUCTS INCLUDING LIABILITY OR WARRANTIES RELATING TO FITNESS FOR A PARTICULAR PURPOSE, MERCHANTABILITY, OR INFRINGEMENT OF ANY PATENT, COPYRIGHT OR OTHER INTELLECTUAL PROPERTY RIGHT.

LIFE SUPPORT POLICY

NATIONAL'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS PRIOR WRITTEN APPROVAL OF THE CHIEF EXECUTIVE OFFICER AND GENERAL COUNSEL OF NATIONAL SEMICONDUCTOR CORPORATION. As used herein:

Life support devices or systems are devices which (a) are intended for surgical implant into the body, or (b) support or sustain life and whose failure to perform when properly used in accordance with instructions for use provided in the labeling can be reasonably expected to result in a significant injury to the user. A critical component is any component in a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system or to affect its safety or effectiveness.

National Semiconductor and the National Semiconductor logo are registered trademarks of National Semiconductor Corporation. All other brand or product names may be trademarks or registered trademarks of their respective holders.

Copyright© 2010 National Semiconductor Corporation

For the most current product information visit us at www.national.com



National Semiconductor Americas Technical Support Center Email: support@nsc.com Tel: 1-800-272-9959

National Semiconductor Europe Technical Support Center Email: europe.support@nsc.com National Semiconductor Asia Pacific Technical Support Center Email: ap.support@nsc.com National Semiconductor Japan Technical Support Center Email: jpn.feedback@nsc.com